

Supereyes Digital Endoscope

User's Manual

(N014, N014J)

Introduction

Thank you for using **Supereyes** Digital Endoscope

Supereyes Digital Endoscope is a new-designed digital endoscope of High-Definition, multi-function, which is easy to operate and high efficient . In order to make you enjoy the fun of using Digital Endoscope, please read this User's Manual.

1. Product Description:

- 1) Speculum: ϕ 9MM
- 2) Picture elements: 640*480 High-Definition display
- 3) 500mm(N014),1000mm(N014J) flexible hose(could be customized)
- 4) Larger capacity battery can be applied

①、⑥brightness adjust ②on/off ③picture capture/delete ④video/confirm ⑤setup/back ⑦、⑧、⑨、⑩ direction button
⑪indicator light ⑫ focus adjust





2, Operation Specification


1) On/off




On: Press “on/off” for 2 seconds to start and indicator light will turn on;

Off: press “on/off” for 2 seconds and indicator light will turn off.




2) Focus adjust: lens aiming at the target object, revolving the focus knob⑤ to make the image clear

3)Lightness adjust: press  to decrease; while press  to increase


4)Taking photos: press  shortly

5) View photos: Press  for 2 seconds to enter photos catalogue while small image displayed on the left of screen and photos list on the right; choose photo by moving direction button; press  to display big sized image; press  to back to previous menu.

6) AV recording: press  1 second to record, repress to save video.

7) View video: press  2 seconds to enter video catalogue while small image displayed on the left of screen and video list on the right; choose photo by moving direction button; press  to display video; press  to back to previous menu.

8)Set: press  to enter set up menu

9) Press  to back to previous menu.

10) Delete: Press  to see dialogue box

11) document read: Start the endoscope and connect it to PC, operate on the mobile equipment; or take out the memory card to read by card reader

12) Reset: press reset button to reset if system halted


13) Memory card: insert by aiming at the card slot; take out by press memory card;

14) Indicator light: turn on when charging

15) Charging: connect endoscope to USB interface, indicator light turns on when charging

16) Change battery: push the battery cover out, change battery, then cover the battery back.

17) Conect TV or monitor: insert the AV audio plug into AV interface of endoscope, then connect AV plug into TV or monitor



N014



N014J

